

NOVA 2 CONNECT

03.6100C

JUST CONNECT

Add the connector matching your battery pack



- BOSCH
- BOSCH GREEN
- DEWALT
- EINHELL
- FEIN
- FESTOOL
- FLEX
- HAZET
- HIKOKI
- INGERSOLL
- MAKITA
- MILWAUKEE
- RIDGID
- SNAP-ON
- WÜRTH



//Powerbank
Built-in power bank
with USB outlet to
charge mobile devices



3
years
warranty*

*go to scangrip.com to register



High efficiency
COB LED



165 lm/W



2000 lm @ 100%
1500 lm @ 75%
1000 lm @ 50%
500 lm @ 25%
200 lm @ 10%



300-3000
lux @0.5m



Compatible with
METABO / CAS
battery system
12V 4.0 Ah - 18V 5.2 Ah
and 15 other
18V battery packs
by using the
SCANGRIP
CONNECTOR



16W



2.5-27h @12V
4.0 Ah battery
5.75-58h @18V
5.2 Ah battery



-10° to +40° C



IK07



1m



IP30



161x164x78 mm



720g



USB power bank:
5V DC / 1A


BATTERY, CHARGER, CONNECTORS AND POWER SUPPLY ARE SOLD SEPARATELY

SCANGRIP CONNECTORS for 18V battery packs



BOSCH - 03.6140C
BOSCH GREEN - 03.6141C
DEWALT - 03.6142C
EINHELL - 03.6143C
FEIN - 03.6144C
FESTOOL - 03.6153C
FLEX - 03.6145C
HAZET - 03.6146C
HIKOKI - 03.6147C
INGERSOLL - 03.6152C
MAKITA - 03.6148C
MILWAUKEE - 03.6149C
RIDGID - 03.6154C
SNAP-ON - 03.6151C
WÜRTH - 03.6150C

Accessories



POWER SUPPLY
03.6123C



CAS BATTERY
12V 4.0 Ah
03.6120



CAS BATTERY
18V 5.2 Ah
03.6121



CAS CHARGER
03.6122

UK NOVA 2 CONNECT

WARNING:


- Always respect applicable legislation for working with electrical equipment in order to reduce the risk of accidents.
- Avoid looking directly into the beam of light, as this will result in dazzling.
- Do not use the lamp near a naked flame.
- The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.
- Luminaire is only suitable for direct mounting on non-combustible surfaces.

USB POWER OUTLET:

- Built-in USB power outlet to charge mobile devices.
- Output: 5V, 1A

USE:

- To turn the lamp on or off, press the A button.
- To increase the brightness, press the B button.
- To decrease the brightness, press the C button.
- When the brightness level is changed, the new value is saved, and the lamp will start at that level the next time it is turned on.



BATTERY COMPLIANCE:

- The work light is designed to be used with Metabo CAS batteries.
- The lamp is also compatible with 3rd party 18V batteries by using the SCANGRIP CONNECT system.
- It will accept the following battery voltages; 12V and 18V.
- It is possible to use a Scangrip power supply instead of a battery.

WARNING - RISK OF FIRE:

- Minimum distance from lighted objects 0.1m



Discarded electrical products must not be disposed of together with household waste. Please use recycling facilities. Ask your local authority or retailer for advice on recycling.