



SUNMATCH 4

03.5657



CCT SCAN - Stepless

USE

Activate the CCT SCAN function to sweep stepless in the interval from 2500K to 6500K. At any point, the CCT SCAN function can be locked.

3
years
warranty*

*go to scangrip.com to register



Stepless dimmer
10-100%

To save battery and avoid the risk of overheating an intelligent built-in system switches turn the lamp to low mode after 3 minutes of use at high mode.



Ultra high CRI+
COB LED
Spot: High power LED



50-500 lm
Spot: 200 lm



700-1400
lux@0.5m
Spot: 5000
lux@0.5m



2500K-6500K
Spot: 4000K



CRI 96+
Spot: 95 CRI



3.7V / 2600mAh
Li-ion



2-10h
Spot: 3h



4h



-10° to +40° C



1m



IK07



IP65



188x58x26mm



267g



Included
USB cable
Charging input
5V DC 1A

UK SUNMATCH 4

WARNING

- Always respect applicable legislation for working with electrical equipment to reduce the risk of accidents.
- Avoid looking directly into the beam of light, as this will result in dazzling.
- Do not use the lamp near a naked flame.
- The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.

USE

- Press the on/off button to turn the lamp on in the sequence: Main > Spot > Off.
- Press and hold the on/off button while the main light is on to start dimming. Release, press, and hold again to increase.
- At the lowest and highest levels, the light will flash until the button is released.
- When the lamp is turned off the lamp will remember the setting of the main light.
- When the light is on, press the CCT SCAN button to change the color temperature manually.
- When the light is on, press and hold the CCT SCAN button for 2 seconds to activate the CCT SCAN mode.
- When in CCT SCAN mode, press the CCT SCAN button to pause the CCT SCAN mode.
- When in CCT SCAN mode, press and hold the CCT SCAN button for 2 seconds to deactivate CCT SCAN mode. When in CCT Scan mode, the CCT indicator corresponds to the following color temperature ranges: 25: 2500-3300K, 35: 3301-4100K, 45: 4101-4900K, 55: 4901-5700K, 65: 5701-6500K.
- To save battery and avoid the risk of overheating an intelligent built-in system turn the lamp to low mode (250 lumen) after 3 minutes of use at high mode (500 lumen).

CHARGING / BATTERY

- During charging, the 4 led bars will indicate the level of charge in red color. When fully charged, all 4 led bars will light up with green color.
- Battery capacity indicator: when the lamp is OFF, press and hold on/off button for 2 sec. (Capacity indicator function is disabled when the lamp is on).
- Use 5V, 1A USB charger.
- Always replace the battery with a new one of the same type and grade.
- Don't leave battery discharged. Otherwise, it could be over-discharged and may NOT be able to be recharged.



Discarded electrical products must not be disposed of together with household waste. Please use recycling facilities. Ask your local authority or retailer for advice on recycling.

- The battery must be removed from the device before it is broken up.
- The device must be disconnected from the mains when the battery is removed.
- Please dispose of the battery safely.